

## THREE LAWS OF GEOMETRICAL OPTICS

Link to: [physicspages home page](#).

To leave a comment or report an error, please use the auxiliary blog.

References: Griffiths, David J. (2007), Introduction to Electrodynamics, 3rd Edition; Pearson Education - Problem 9.15.

We got the equations for reflected and transmitted waves when an electromagnetic wave is incident on a boundary head-on. Using similar (although somewhat more involved) methods, we can solve the general case where a wave is incident on a boundary at any angle.

Suppose the wave vector of the incident wave is  $\mathbf{k}_I$  and the boundary is located on the  $xy$  plane. The incident wave is

$$(0.1) \quad \tilde{\mathbf{E}}_I = \tilde{\mathbf{E}}_{0I} e^{i(\mathbf{k}_I \cdot \mathbf{r} - \omega t)}$$

$$(0.2) \quad \tilde{\mathbf{B}}_I = \frac{1}{v_1} \hat{\mathbf{k}}_I \times \tilde{\mathbf{E}}_I$$

where the direction of polarization is given by the direction of  $\tilde{\mathbf{E}}_{0I}$ . At this stage, we don't know the direction of either the reflected or transmitted waves, so we can just write them as

$$(0.3) \quad \tilde{\mathbf{E}}_R = \tilde{\mathbf{E}}_{0R} e^{i(\mathbf{k}_R \cdot \mathbf{r} - \omega t)}$$

$$(0.4) \quad \tilde{\mathbf{B}}_R = \frac{1}{v_1} \hat{\mathbf{k}}_R \times \tilde{\mathbf{E}}_R$$

$$(0.5) \quad \tilde{\mathbf{E}}_T = \tilde{\mathbf{E}}_{0T} e^{i(\mathbf{k}_T \cdot \mathbf{r} - \omega t)}$$

$$(0.6) \quad \tilde{\mathbf{B}}_T = \frac{1}{v_2} \hat{\mathbf{k}}_T \times \tilde{\mathbf{E}}_T$$

The speeds  $v_i$  of the waves are determined by the medium and not by the direction of the waves and since the frequency  $\omega$  is the same for all three waves and  $\omega = kv$ , we get

$$(0.7) \quad k_I v_1 = k_R v_1$$

$$(0.8) \quad k_I = k_R$$

$$(0.9) \quad k_I v_1 = k_T v_2$$

$$(0.10) \quad k_T = \frac{v_1}{v_2} k_I = \frac{n_2}{n_1} k_I$$

where  $n_i$  is the index of refraction.

This gives us the magnitudes of the wave vectors, but not the directions. To get those, we need to apply the boundary conditions for zero surface charge:

$$(0.11) \quad \epsilon_1 E_1^\perp - \epsilon_2 E_2^\perp = 0$$

$$(0.12) \quad B_1^\perp - B_2^\perp = 0$$

$$(0.13) \quad \mathbf{E}_1^\parallel - \mathbf{E}_2^\parallel = 0$$

$$(0.14) \quad \frac{1}{\mu_1} \mathbf{B}_1^\parallel - \frac{1}{\mu_2} \mathbf{B}_2^\parallel = 0$$

where the subscript 1 refers to fields in medium 1 ( $z < 0$ ) and 2 refers to medium 2 ( $z > 0$ ). That is

$$(0.15) \quad \mathbf{E}_1 = \mathbf{E}_I + \mathbf{E}_R$$

$$(0.16) \quad \mathbf{E}_2 = \mathbf{E}_T$$

and similarly for  $\mathbf{B}$ . Thus all these boundary conditions have the form

$$(0.17) \quad A_I e^{i(\mathbf{k}_I \cdot \mathbf{r} - \omega t)} + A_R e^{i(\mathbf{k}_R \cdot \mathbf{r} - \omega t)} = A_T e^{i(\mathbf{k}_T \cdot \mathbf{r} - \omega t)}$$

for coefficients  $A_i$  that vary, depending on the boundary condition being imposed, but that don't depend on  $\mathbf{r}$  or  $t$ . The space and time dependencies are entirely within the complex exponentials. Since we've taken the boundary to be the  $xy$  plane,  $z = 0$  in these equations, so they become

$$(0.18) \quad A_I e^{i(k_{Ix}x + k_{Iy}y - \omega t)} + A_R e^{i(k_{Rx}x + k_{Ry}y - \omega t)} = A_T e^{i(k_{Tx}x + k_{Ty}y - \omega t)}$$

$$(0.19) \quad A_I e^{i(k_{Ix}x + k_{Iy}y)} + A_R e^{i(k_{Rx}x + k_{Ry}y)} = A_T e^{i(k_{Tx}x + k_{Ty}y)}$$

These equations must be valid over the entire  $xy$  plane, so they are valid for  $x = 0$  or  $y = 0$ :

$$(0.20) \quad A_I e^{ik_{Ix}x} + A_R e^{ik_{Rx}x} = A_T e^{ik_{Tx}x}$$

To see what this implies, consider the general case

$$(0.21) \quad A e^{iax} + B e^{ibx} = C e^{icx}$$

for all  $x$ . That is, both sides are the same function of  $x$ , so they must have the same Taylor expansion. Starting at point  $x$  and expanding to get the function at  $x + \Delta x$  we get up to first order in  $\Delta x$ :

$$(0.22) \quad Ae^{iax}(1 + ia\Delta x) + Be^{ibx}(1 + ib\Delta x) + \mathcal{O}(\Delta x^2) = Ce^{icx}(1 + ic\Delta x) + \mathcal{O}(\Delta x^2)$$

Using 0.21 and cancelling common factors we get

$$(0.23) \quad aAe^{iax} + bBe^{ibx} = cCe^{icx}$$

$$(0.24) \quad = c(Ae^{iax} + Be^{ibx})$$

$$(0.25) \quad A(a - c)e^{iax} + B(b - c)e^{ibx} = 0$$

This last equation must be true for all  $x$  so we must have

$$(0.26) \quad a = b = c$$

Going back to 0.19, we therefore must have

$$(0.27) \quad k_{Ix} = k_{Rx} = k_{Tx}$$

$$(0.28) \quad k_{Iy} = k_{Ry} = k_{Ty}$$

If we choose axes so that  $\mathbf{k}_I$  is in the  $xz$  plane, then  $\mathbf{k}_R$  and  $\mathbf{k}_T$  must also lie in the same plane. This gives the first law of geometrical optics:

The wave vectors of the incident, reflected and transmitted waves all lie in the same plane, and this plane also contains the normal to the boundary.

If the angle of incidence is  $\theta_I$  (that is, the angle between  $\mathbf{k}_I$  and the normal to the  $xy$  plane) with  $\theta_R$  and  $\theta_T$  the corresponding angles for reflection and transmission, then from 0.8 we have

$$(0.29) \quad k_I \sin \theta_I = k_R \sin \theta_R$$

$$(0.30) \quad = k_I \sin \theta_R$$

$$(0.31) \quad \sin \theta_I = \sin \theta_R$$

$$(0.32) \quad \theta_I = \theta_R$$

This is the familiar condition for specular reflection: the angle of incidence is equal to the angle of reflection. This is the second law of geometrical optics.

Finally, for the transmitted wave, from 0.10 we have

$$(0.33) \quad k_I \sin \theta_I = k_T \sin \theta_T$$

$$(0.34) \quad = \frac{n_2}{n_1} k_I \sin \theta_T$$

$$(0.35) \quad \frac{\sin \theta_I}{\sin \theta_T} = \frac{n_2}{n_1}$$

This is Snell's law, or the law of refraction, which is the third law of geometrical optics.

We haven't actually applied the boundary conditions yet, apart from 0.20, but we'll look at that next to get an idea of the reflection and transmission coefficients.

#### PINGBACKS

Pingback: [Fresnel equations for perpendicular polarization](#)

Pingback: [Total internal reflection](#)

Pingback: [Lensmaker's equation](#)