

## WAVE GUIDES: DERIVATION OF THE WAVE EQUATION

Link to: [physicspages home page](#).

To leave a comment or report an error, please use the [auxiliary blog](#).

References: Griffiths, David J. (2007), Introduction to Electrodynamics, 3rd Edition; Pearson Education - Problem 9.26.

A wave guide is a hollow tube which allows electromagnetic waves to travel down it. Wave guides are usually made of conductors, so we'll assume that they are made of a perfect conductor so that  $\mathbf{E} = 0$  everywhere inside the conducting boundary.

The boundary conditions implied by Maxwell's equations are

$$(0.1) \quad \epsilon_1 E_1^\perp - \epsilon_2 E_2^\perp = \sigma_f$$

$$(0.2) \quad B_1^\perp - B_2^\perp = 0$$

$$(0.3) \quad \mathbf{E}_1^\parallel - \mathbf{E}_2^\parallel = 0$$

$$(0.4) \quad \frac{1}{\mu_1} \mathbf{B}_1^\parallel - \frac{1}{\mu_2} \mathbf{B}_2^\parallel = \mathbf{K}_f \times \hat{\mathbf{n}}$$

In particular, 0.3 tells us that the parallel component of  $\mathbf{E}$  is zero at the boundary of the wave guide. As usual, we'll take the  $z$  axis to be parallel to wave guide's axis, so the waves have the form

$$(0.5) \quad \tilde{\mathbf{E}} = \tilde{\mathbf{E}}_0(x, y) e^{i(kz - \omega t)}$$

$$(0.6) \quad \tilde{\mathbf{B}} = \tilde{\mathbf{B}}_0(x, y) e^{i(kz - \omega t)}$$

Maxwell's equations inside the guide (assumed to be a vacuum) are

$$(0.7) \quad \nabla \cdot \mathbf{E} = 0$$

$$(0.8) \quad \nabla \cdot \mathbf{B} = 0$$

$$(0.9) \quad \nabla \times \mathbf{E} = -\frac{\partial \mathbf{B}}{\partial t}$$

$$(0.10) \quad \nabla \times \mathbf{B} = \frac{1}{c^2} \frac{\partial \mathbf{E}}{\partial t}$$

Previously, we applied the divergence equations to show that the waves were transverse (no  $z$  component), but that relied on the waves being unbounded plane waves, which is not the case here. It turns out that waves in

a wave guide are not transverse in general, in that at least one of  $\mathbf{E}$  and  $\mathbf{B}$  must have a longitudinal component. We therefore write

$$(0.11) \quad \tilde{\mathbf{E}}_0(x, y) = E_x \hat{\mathbf{x}} + E_y \hat{\mathbf{y}} + E_z \hat{\mathbf{z}}$$

$$(0.12) \quad \tilde{\mathbf{B}}_0(x, y) = B_x \hat{\mathbf{x}} + B_y \hat{\mathbf{y}} + B_z \hat{\mathbf{z}}$$

where all the components on the RHS depend on  $x$  and  $y$ , and may be complex functions. Putting these together with 0.5 and 0.6 into 0.9, we get (remembering that the components do not depend on  $z$ ):

$$(0.13) \quad \nabla \times \mathbf{E} = (\partial_y E_z - ikE_y) \hat{\mathbf{x}} + (-\partial_x E_z + ikE_x) \hat{\mathbf{y}} + (\partial_x E_y - \partial_y E_x) \hat{\mathbf{z}}$$

$$(0.14) \quad = -\frac{\partial \mathbf{B}}{\partial t}$$

$$(0.15) \quad = i\omega B_x \hat{\mathbf{x}} + i\omega B_y \hat{\mathbf{y}} + i\omega B_z \hat{\mathbf{z}}$$

Equating components, we get

$$(0.16) \quad \partial_y E_z - ikE_y = i\omega B_x$$

$$(0.17) \quad -\partial_x E_z + ikE_x = i\omega B_y$$

$$(0.18) \quad \partial_x E_y - \partial_y E_x = i\omega B_z$$

We can apply exactly the same procedure to 0.10 to get the analogous equations

$$(0.19) \quad \partial_y B_z - ikB_y = -i\frac{\omega}{c^2} E_x$$

$$(0.20) \quad -\partial_x B_z + ikB_x = -i\frac{\omega}{c^2} E_y$$

$$(0.21) \quad \partial_x B_y - \partial_y B_x = -i\frac{\omega}{c^2} E_z$$

We can solve these 6 equations to get the  $x$  and  $y$  components in terms of the  $z$  components. For example, multiplying 0.17 through by  $k$  and 0.19 through by  $\omega$  and adding, we get

$$(0.22) \quad -k\partial_x E_z + ik^2 E_x - i\frac{\omega^2}{c^2} E_x = \omega\partial_y B_z$$

$$(0.23) \quad E_x = \frac{1}{i(k^2 - \omega^2/c^2)} (k\partial_x E_z + \omega\partial_y B_z)$$

$$(0.24) \quad = \frac{i}{\omega^2/c^2 - k^2} (k\partial_x E_z + \omega\partial_y B_z)$$

Similarly, we can get the other 3 equations. Multiply 0.16 by  $k$  and 0.20 by  $\omega$  and subtract to get

$$(0.25) \quad E_y = \frac{i}{\omega^2/c^2 - k^2} (k\partial_y E_z - \omega\partial_x B_z)$$

Multiply 0.16 by  $\omega/c^2$  and 0.20 by  $k$  and subtract to get

$$(0.26) \quad B_x = \frac{i}{\omega^2/c^2 - k^2} \left( k\partial_x B_z - \frac{\omega}{c^2} \partial_y E_z \right)$$

Multiply 0.17 by  $\omega/c^2$  and 0.19 by  $k$  and add to get

$$(0.27) \quad B_y = \frac{i}{\omega^2/c^2 - k^2} \left( k\partial_y B_z + \frac{\omega}{c^2} \partial_x E_z \right)$$

To get the wave equations we can apply 0.7 and 0.8:

(0.28)

$$\nabla \cdot \mathbf{E} = \frac{i}{\omega^2/c^2 - k^2} [(k\partial_{xx} E_z + \omega\partial_{yx} B_z) + (k\partial_{yy} E_z - \omega\partial_{xy} B_z)] + ikE_z$$

$$(0.29) \quad = \frac{i}{\omega^2/c^2 - k^2} [k\partial_{xx} E_z + k\partial_{yy} E_z] + ikE_z$$

$$(0.30) \quad = 0$$

The wave equation for  $E_z$  is thus

$$(0.31) \quad [\partial_{xx} + \partial_{yy} + \omega^2/c^2 - k^2] E_z = 0$$

Exactly the same procedure applied to  $\nabla \cdot \mathbf{B} = 0$  gives

$$(0.32) \quad [\partial_{xx} + \partial_{yy} + \omega^2/c^2 - k^2] B_z = 0$$

Solving these two equations subject to the boundary conditions will give us all 3 components of each field.

#### PINGBACKS

Pingback: Rectangular wave guides: transverse electric waves

Pingback: Wave guide: energy flows at the group velocity

Pingback: Rectangular resonant cavity